Navilock NL-8003P MD6 Serial PPS Multi GNSS Receiver u-blox 8 1.5 m

Popis

The MD6 serial multi GNSS Receiver based on u-blox 8 chipset has a built-in antenna for high sensitivity. You can use this GNSS Receiver with a notebook and a suitable routing software for navigation. The MD6 universal connector enables the connection of optional USB or serial connecting cables.



Číslo produktu 62525

EAN: 4043619625253

Země původu: Taiwan, Republic of China

Balení: Kartonová krabice

Specifikace

- Connector:
  MD6 Navilock plug (RS-232) (USB or serial cable are optional available)
- u-blox 8 UBX-M8030-KT chipset
- Frequency:
  GPS: L1, 1575.4200 MHz
  GLONASS: L1, 1602 (k x 0,5625) MHz
  BEIDOU COMPASS: B1, 1561.0980 MHz
  GALILEO E1, 1575.4200 MHz
  QZSS L1, 1575.4200 MHz
- Accepts the signals of up to 72 satellites at the same time
- Supports AssistNow online/offline,
  SBAS (WAAS, EGNOS, QZSS and MSAS)
- Supports NMEA 0183 protocols: GGA, GSA, GSV, RMC, VTG
- Auto Baud Rate up to 115200 bps
- PPS signal on pin 6 (LVTTL 3.3 V)
- Update rate:
  single GNSS: 18 Hz (e.g. GPS solo)
  multi GNSS: 10 Hz (e.g. GPS+GLONASS)
- Sensibility max. –167 dBm
- IPX6 protection class
- Magnetic, non-slip on the bottom
- LED-indicator for GPS-status
- Operating temperature: -20 °C ~ 60 °C

© 2024 by Navilock. Všechny názvy a symboly zde uvedené jsou vlastnictvím výrobce.
Tiskové chyby, změny a chyby v datech vyhrazeny.

- Power supply: 5 Volt
- Current consumption: max. 45 mA
- Cold start in ca. 26 seconds
- Hot start in ca. 1 second
- Positioning accuracy: 2.5 m CEP (Circular Error Probable) and 2 m CEP with SBAS
- Cable length: ca. 1.5 m
- Dimensions (LxWxH): ca. 65 x 45 x 22 mm

Systémové požadavky

- Windows Vista/7/8/8.1/10, Linux Kernel 2.6, Mac OS X
- MD6 connection cable

Obsah balení

- MD6 serial receiver
- Driver CD
- User manual on CD ROM

Příslušenství



© 2024 by Navilock. Všechny názvy a symboly zde uvedené jsou vlastnictvím výrobce.
Tiskové chyby, změny a chyby v datech vyhrazeny.